

CEL-FI SOLO

3G / 4G / 5G

Smart Signal Booster™

DATA SHEET

MODEL NUMBER:
H41-9X-XXX
H41-AX-XXX

The Cel-Fi SOLO Smart Signal Booster is designed to solve cellular coverage problems for voice and data. With up to 100 dB of gain, it is the most powerful carrier grade solution available. The Cel-Fi SOLO covers up to 1,500 square meters of indoor space per system. Configure with included donor and server antennas, or expand options with outdoor or multiple server antennas. The Nextivity commitment is to protect the operator's network, deliver the best cellular performance, and be the easiest solution to install.



CEL-FI SOLO



CEL-FI SOLO
WITH LTE MODEM

Benefits:

- Boosts cellular coverage
- Data and Voice support, in one solution
- Deploy the unit anywhere in the network, with full frequency coverage
- Up to 1,500 m² coverage area



Use **Cel-Fi WAVE** mobile application to aim an external antenna and ensure an optimal donor signal.



System Features

Smart Signal Booster™

Multiple Installation options supported.

LED User Indicators for Status

Simple, built-in, self-test

Unlocked: Cell phones do not need to be registered

Support for Cel-Fi WAVE mobile application

End-to-end cellular communication encryption without additional risk of vulnerability

Convection cooling

Optional: Integrated category 1 LTE modem for remote management (H41-xC-xxx variants include modem)

Wireless Features

Carrier Grade, Smart Signal Booster

3G / 4G / 5G

100 dB gain

Five (5) RF front ends (check model number for bands specifics)

60 MHz relay bandwidth

Relays three (3) channels simultaneously (up to 20 MHz each)

Can simultaneously relay two (2) Band 1 signals // 3G and 4G LTE

SMA RF Connectors for Donor and Server, for flexible deployment

Mobile Network and Network Protection Features

Supports multiple channels with bandwidths of 5/10/15/20 MHz per channel

Works with any user equipment (UE) on the configured network (no whitelist/blacklist)

Provider-specific system: Cel-Fi distributes and boosts service only for the Operator PLMN-IDs for which the device is authorized and configured

Secure and ciphered provisioning

System intelligence accurately establishes proper safe uplink power in real time

Uplink Muting Mode automatically shuts down uplink cellular transmissions when no active user equipment is detected

System shuts down upon Operator's network command or failure detection

Nextivity purpose-built, high-performance, six core ASIC processor, provides best performance at lowest cost

Wireless Benefits

Distribute and boost cellular coverage

3G, 4G and 5G support, Voice and Data, network safe

LED cues provide visual feedback for ease of setup and status

Works with any subscriber device from the designated Operator

Supports peaceful co-existence with guard band NB-IoT deployments

System Benefits

Clear and reliable cellular connections within coverage area up to 15,000 ft² (1,500 m²) per system

Highest gain (100 dB) provides best coverage footprint

Advanced Echo-Cancellation allows Cel-Fi to transmit more power without feedback interference

Subscriber devices (UE) require less transmit power for improved battery life

Linearity eliminates IMD desense issues

Dynamic gain control ensures maximum gain – best coverage – at all times in ever changing RF environments, without user intervention

Mobile Network Benefits Flexibly deploy on LTE, VoLTE, LTE-Advanced, NB-IoT and WCDMA networks, with multiple cellular bands, simultaneously
Automatically adjusts channel bandwidths between 5 MHz and 20 MHz
UE control is transparent and remains centralized in the network core (no gateways or third-party software)

Compliance 3GPP TS 25.143
(check individual product regional compliance) 3GPP TS 36.143
Bluetooth BQB
CE
ACMA (Australia)
R-NZ (New Zealand)

System Management Via Cel-Fi WAVE cloud portal
(Software) Cel-Fi WAVE Portal capability:

- Status (list and map)
- Commissioning
- Diagnostics
- Software Updates
- Settings
- Reporting
- Alarms & Notifications

Antenna Ports Impedance: 50 Ohms
(Donor and Server) Port-to-port Isolation: >110 dB
Connector: SMA FEMALE
Return Loss: <-8 dB

Environmental Operating temperature: 0°C to 50°C
Convection Cooling
Relative humidity: 0% to 95%, non-condensing
RoHS (European and China compliant)
CE
IP Rating: 20

Power Consumption 40W
(max)

Dimensions	Height	Width	Length	Weight
	186 mm	186 mm	127 mm	1.8 kg

Installation Wall-mounting hardware included

Downlink Power		Uplink Power	
All Bands	20 dBm	Bands 1, 3, 7	22 dBm
		Bands 5, 8, 20, 28L	20 dBm

Radio Noise Figure: 7 dB
Return Loss: -8 dB

Group Delay LTE 5 MHz = 5.5 us
LTE 10 MHz, 15 MHz, 20 MHz = 5.5 us
WCDMA = 7.5 us

Band Variations:
Model #: H41-9X-XXX
1, 3, 7, 8, 20

Band	Downlink	Uplink	Bandwidth
1	2110–2170 MHz	1920–1980 MHz	Up to 20 MHz per carrier, 2 carriers
3	1805–1880 MHz	1710–1785 MHz	Up to 20 MHz per carrier, 1 carrier
7	2620–2690 MHz	2500–2570 MHz	Up to 20 MHz per carrier, 1 carrier
8	925–960 MHz	880–915 MHz	Up to 15 MHz per carrier, 1 carrier
20	791–821 MHz	832–862 MHz	Up to 20 MHz per carrier, 1 carrier

Band Variations:
Model #: H41-AX-XXX
1, 3, 5, 8, 28L

Band	Downlink	Uplink	Bandwidth
1	2110–2170 MHz	1920–1980 MHz	Up to 20 MHz per carrier, 2 carriers
3	1805–1880 MHz	1710–1785 MHz	Up to 20 MHz per carrier, 1 carrier
5	869–894 MHz	824–849 MHz	Up to 20 MHz per carrier, 1 carrier
8	925–960 MHz	880–915 MHz	Up to 15 MHz per carrier, 1 carrier
28L	758–788 MHz	703–733 MHz	Up to 20 MHz per carrier, 1 carrier

Copyright © 2021 by Nextivity, Inc, U.S. All rights reserved. The Nextivity and Cel-Fi logos are registered trademarks of Nextivity Inc. All other trademarks or registered trademarks listed belong to their respective owners. Designed by Nextivity in California. data_solo_eur_21-0406